



Type A Camlock - Male Camlock / Female BSP

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	21	21	24	28.5	36	45	56.5	73	98
B	38	38	48	56	60	64	87	73	78
C	32	32	40	48	56	67	83	96	127

Type B Camlock - Female Camlock / Male BSP

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	14	14	24	28	35	51	58	72	98
B	52	52	64	72	73	80	90	94	101
E	32	32	40	48	49	54	59	60	62
G	53	53	60	78	85	96	110	127	156

Type C Camlock - Female Camlock / Male Hosebarb

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	14	14	20	25	31	43	55	67	92
B	92	92	105	118	121	138	155	164	175
D	20	20	26	33	39	52	65	77	103
E	32	32	40	48	49	54	59	60	62
G	53	53	60	78	85	96	110	127	156

Type D Camlock - Female Camlock / Female BSP

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	16	19	26	30	39	50	58	72	98
B	52	52	62	68	71	78	85	91	96
C	32	32	40	48	56	67	83	96	127
E	32	32	40	48	49	54	59	60	62
G	53	53	60	78	85	96	110	127	156

Type E Camlock - Male Camlock / Male Hosebarb

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	14	19	24	28	35	48	58	72	98
B	98	98	110	121	125	140	158	170	182
D	20	20	26	33	39	52	65	77	103
E	40	40	46	53	56	61	65	66	70
C	34	34	38	48	56	66	80	102	132

Type F Camlock - Male Camlock / Male BSP

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	21	21	24	28.5	36	45	56.5	73	98
B	56	56	72	80	84	88	100	106	114
C	32	32	40	48	56	67	83	96	127
E	39	39	48	56	61	62	69	74	79

Type DC Camlock - Dust Cap

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
B	45	45	54	65	69	80	84	85	94
E	32	32	40	48	49	54	59	60	62
G	53	53	60	78	85	96	110	127	156

Type DP Camlock - Dust Plug

Dimensions	1/2"	3/4"	1"	1 1/4"	1 1/2"	2"	2 1/2"	3"	4"
in millimetres	15	20	25	32	40	50	65	80	100
A	21	21	24	29	36	45	57	73	98
B	37	37	44	55	64	68	70	80	80
E	24	24	30	38	41	43	45	52	48